

Link do produktu: <https://cb-radia.pl/retevis-rt3s-gps-vhfuhf-5w-radiotelefon-dmr-tier2-gratis-etui-do-wyczerpania-zapasow-p-1353.html>



Retevis RT3S GPS VHF/UHF 5W Radiotelefon DMR Tier2 * + Gratis ETUI do wyczerpania zapasów

Cena	555,00 zł
Dostępność	Dostępny
Czas wysyłki	24 godziny
Producent	Retevis

Opis produktu

Promocja 2024

PHU ARTURSSS jako dystrybutor Retevis na Polskę w ofercie koniec zimy 2024 do każdego radia Gratis ETUI

Retevis RT3S

Dwuzakresowe cyfrowe radio krótkofalowe RT3S wykorzystuje protokół Digital Mobile Radio (DMR) Tier 2 Standard. Jest kompatybilny z popularną serią MOTO TRBO Tier I i II przy użyciu standardowego szyfrowania, jest również kompatybilny z dowolnym istniejącym analogowym radiotelefonem działającym na obsługiwanych częstotliwościach UHF i VHF w celu łatwej migracji do technologii cyfrowej.

General specifications

Frequency	136-174&400-480MHz
Channels	3000
Frequency Stability	±1ppm
Operating Temperature	-30°C~+60°C
Operating Voltage	7.4V DC
Dimension	131 x 61 x 36mm
Weight	258g (with battery)
Battery Type	Li-ion
Battery Capacity	2000mAh
Antenna Impedance	50Ω
Audio Impedance	1W@16Ω
Channel Spacing	12.5KHz
Vocoder	AMBE+2™
Transmitter	
Power	High≤5W, Low≤1W
Frequency Stability	±1.0ppm
Adjacent Channel Power	≤-60dB
Free Time Slot Power	TDMA:≤57dBm
Hum and noise	-40dB@12.5KHz
Spurious radiation	Antenna:9KHz-1GHz ≤-36dBm 1GHz-12.75GHz ≤-30dBm
FM modulation mode	11K0F3E@12.5KHz
4FSK digital mode	12.5KHz(data only):7K60FXD12.5KHz(data and voice):7K60FXW
Modulation maximum deviation	2.5KHz@12.5KHz
Nonactive slot power	-57dBm
Digital Protocol	ETSI-TS102 361-1,-2,-3
Audio Response	+1~-3dB
Modulation BER(bit error rate)	≤5%
Receiver	
Analog Sensibility	0.2μV@12dB SINAD
Digital Sensibility	0.25μV(BER:5%)
Adjacent Channel Selectivity	≤-60dB@12.5KHz
Intermodulation	≤60dB
Spurious Response	≥70dB
Audio Response	+1~-3dB



P.H.U. ARTURSSS

Artur Wyciszkiewicz
Gomulińskiego 5/37
05-804 Pruszków
Tel. 508194227

Rated Audio Distortion
Rated Audio Power
Modulation

□5%
1W
≥45dB@25KHz≥40dB@12.5KHz